

Change CCR Tree



CJ Tel Communications Ltd.
For Sales or Service Call: (403) 274-7774
info@cjtelcommunications.com

Figure 1

Step 1 – Disable CCR Tree

Feature 983

Log: 120000 or 1020000

Admin
MBOX AA OTHR

Auto Atdt Admin
GRTG TABLE LINES

Grtg Table: 1
RETRY OK

AA Menu Prompt: N
CHNG REC OK

Morning: 1, 2, 3, 4 (consecutive)
CHNG PLAY NEXT

Afternoon: 1, 2, 3, 4 (consecutive)
CHNG PLAY NEXT

Evening: 1, 2, 3, 4 (consecutive)
CHNG PLAY NEXT

Non-Business: 1, 2, 3, 4 (consecutive)
CHNG PLAY NEXT

Lang pref: pri
CHNG NEXT

Atdt: 221
CHNG NEXT

Morn CCR Tree: 1
CHNG OK

Morn CCR Tree: NO
DISABLE OK

Aftn CCR Tree: 1
CHNG OK

Aftn CCR Tree: NO
DISABLE OK

Eve CCR Tree: 1
CHNG OK

Eve CCR Tree: NO
DISABLE OK

NBus CCR Tree: 1
CHNG OK

NBus CCR Tree: NO
DISABLE OK

Press *

Continue to next step ...

Change CCR Tree

Step 2 – Change CCR Tree

Admin
MBOX AA OTHR

Admin
GLIST CCR

CCR Admin
ADMIN

CCR Tree: 1
RETRY OK

Tree: 1
CHNG PRINT QUIT

Path: (0 – 8) ←
(0 = Main Menu Recording)
(1 – 8 = Tree options)
RETRY END OK

0 Home/Menu
REC OTHR OK

Primary rec?
REC PLAY NEXT

Primary rec?
REC PLAY NEXT

Rec pri prompt:
RETRY OK

Accept prompt?
RETRY PLAY OK

Press * **OR Return to -^**

RETRY END OK

Tree: 1
SAVE PRINT QUIT

Save as Tree 1
YES OTHR QUIT

Tree Saved
Press * *

Continue to next step ...

Change CCR Tree

Step 3 – Enable CCR Tree

Admin
MBOX AA OTHR

NBus CCR Tree: 1
Enable OK

Auto Atdt Admin
GRTG TABLE LINES

Rls

Grtg Table: 1
RETRY OK

AA Menu Prompt: N
CHNG REC OK

Morning: 1, 2, 3, 4 (consecutive)
CHNG PLAY NEXT

Afternoon: 1, 2, 3, 4 (consecutive)
CHNG PLAY NEXT

Evening: 1, 2, 3, 4 (consecutive)
CHNG PLAY NEXT

Non-Business: 1, 2, 3, 4 (consecutive)
CHNG PLAY NEXT

Lang pref: pri
CHNG NEXT

Atdt: 221
CHNG NEXT

Morn CCR Tree: NO
CHNG OK

Morn CCR Tree: 1
Enable OK

Aftn CCR Tree: NO
CHNG OK

Aftn CCR Tree: 1
Enable OK

Eve CCR Tree: NO
CHNG OK

Eve CCR Tree: 1
Enable OK

NBus CCR Tree: NO
CHNG OK